Installation Instructions for Mirial Softphone Mac OS 10.5-10.6

Before you begin please be sure that you have administrative privileges to install the software on your computer. If you do not, please contact your system administrator.

You will be provided with a license file for Mirial Softphone by the College of Arts and Sciences Computer Support office. If you have not received your license code please contact <u>techsupport@mail.as.miami.edu</u> or call (305) 284-4223.

Requirements: Mac OSX 10.5 or 10.6, webcam, microphone, speaker, high-speed internet access

<section-header><image><image><section-header><section-header><section-header><section-header><section-header><section-header><section-header><section-header><section-header><section-header><section-header>

Download the software from <u>www.as.miami.edu/support/lifesize</u> After you have downloaded the installer, double-click on the file.

Select "Continue"



Click "Continue"



Select "Agree"



Select "Install" to install in the default Applications Folder



Select "Continue"



Select "Install"



You will be prompted to provide your administrator credentials. Type in your password and select "OK".



Select "Close"

\bigcirc 4	3.	*			Thι	9:1	19 AN	1	Q
Spotlight	so	oft							8
		Sho	w Al	II					
Top Hit		Miri	ial S	oft	pho	ne			
Definition	<u>.</u>	adje	ectiv	/e	1 ea	asy to	o molo	d, (:u
Applications	<u></u>	Miri	ial So	oft	pho	ne			
System Preferences	2	Sou	nd						
	2	Soft	twar	e l	Jpda	ate			
Documents	e 1	Miri	ialSo	oftp	ohor	ne-ir	stalle	r.p	kg
		defa nun	ault. neric	.kb c.k	map hma) In			
Messages	ė.	Anr	ole C	live	oc Si	neak	Peek	of	м
incosageo	2 F	FW:	Gra	dP	lan	orde	r for T	elı	m
PDF Documents	🛐 I	FMF	PA Li	ice	nse	(Eng	lish).p	df	
		FMF	P Rea	ad	Me	(Eng	lish).p	df	
	<u></u>	FMF	' Acl	kno	owle	dgei	ments	.pc	1t
Webpages	8 I	Fail miri	ed to ial so	o c oft	pen	pag	e — H	list Ie	s
		Fail	ed to	0 0	pno	pag	le — H	list	ory
	e 1	Fail	ed to	0 0	open	pag	e — H	list	ory
Fonts	2	Сор	per	pla	te C	iothi	c Ligh	t	
	 Image: A state Image: A state<th>Cop</th><th>per</th><th>pla</th><th>ite C</th><th>iothi</th><th>c Bold</th><th></th><th></th>	Cop	per	pla	ite C	iothi	c Bold		
		-	per	DI	auk				
	2	spo	tligh	nt I	Prefe	eren	ces		

Open your "Applications" folder and double-click on the "Mirial Softphone" icon or search for "Mirial" in using "spotlight" and select the application from the list.





Locate and select the file that was saved to the "Desktop" ending with .lic Highlight it and then select "Open".

	Type your password to allow Mirial Softphone to make changes.
	Name: Computer Support Password:
10	(?) (Cancel OK
	MITHIC

Type in your administrator password and Select "OK"



Select the checkbox for "I have read the license..." and then select "OK".



The "General" configuration settings window will appear leave the default as is and select "Next".

ß	General	Video	Audio	Codecs	Network	SIP	H.323
	Device:	Built-in	iSight	Advanced river Setting		•	
0						Prev	Next

Click "Next"

udia (Video		Misc	
RX TX .723.1 ✓ .711A ✓ .711U ✓ .722.1/C ✓	H.261 H.263 H.264	RX TX Enable H.224 H.239 H.239 Adv.		
	SQCIF (128x96) QCIF (176x144) CIF (352x288) 4CIF (704x576) 720p (1280x720) 1080p(1920x1080)			

Click "Next".

Genera	Video Audio	Codecs	Network	SIP H.32
	Telephony Protocols			
	M.323 (ITU-T)	C RTSP	(RFC-2326)	
	IP Network Settings			
	IP network type:	LAN 3	84k 🛟	
	Receive kbps:	384		
	Transmit kbps:	384		
	Automatic Input Ban	dwidth Control vanced)		

Click "Next"

General Video Aud	io Codecs Network	SIP H.323
SIP User:		
Local SIP URI:	sip:@computer-supports-image	local.
Local port:	5060 Adv	anced
Display Name:		
Media Encryption policy:	Disabled	\$
Use Registrar		
Use Outbound Proxy		

Click "Next"

N-8	100	in a bort	mone com	gurution		_
Genera	l Video	Audio	Codecs	Network	SIP	H.323
		F				
Pho	ne number:	r				
Gat	ekeeper / Gate	way				_
	Use Gatekeepe	r				
	Use Gateway					
	Disable Early H	245				
H24	5 Tunneling:	Disable	†			
				<u> </u>		<u></u>
				Œ	rev	Don

Click "Done"



Type in the destination IP address in the available field. The IP address is 129.171.61.85. Click on the green button and wait to be connected.

Please Note: Once connected there will be 10 second delay before the video and audio become available.



Once connected your screen should like image above.

Below is a helpful quick list of the buttons and features available with Mirial SoftPhone.





You can share your presentation or screen by selecting the "Presentation" button and then selecting the appropriate screen from the provided list of active applications and processes.



Additionally, you can record your video conference call by pressing "Record" button on the window that displays your video as indicated above.



When you are finished recording your session deselect the "Record" button and then the select the "Record Calls" button and your video session will be displayed. You have the option to export the video as a .mov file which is playable through Apple QuickTime and saved to your designated folder.

Please remember to <u>uninstall</u> LifeSize Desktop Software after your session has ended as we have a limited amount of licenses. You can do this by dragging and dropping the "Mirial Softphone" file from your "Applications" folder to the Trash Bin and empty it.